



# FMC-CH17

## Simple Converter Chassis

The FMC-CH17 is a 2U high 19" 17 slots chassis. The chassis provides an economic solution in low density fiber converter installations where no management features are required. Each FMC or VDTU2A-301 converter is an independent Ethernet to fiber or Ethernet to copper media converter that may be used as a stand-alone converter or placed in the FMC-CH17 chassis. With two power supplies, the FMC-CH17 chassis supports redundant power from any of two power options. The AC supplies operate from (100-240VAC) and DC supplies operate from 36-60VDC. The built in cooling fan ensures that the temperatures in the rack remain within the tolerated working range.

### Features

- FMC-CH17, 2U, 19", 17-Slot chassis with single or dual built-in power for AC or DC
- Cross flow cooling fan built-in.
- Designed for 19" Rack mounting
- FMC units are hot swappable

### Specifications

<b>Power Input</b>	AC : 100 ~240V or DC : 36 ~ 60V
<b>Power Consumption</b>	<60W
<b>Dimensions</b>	199 x 476 x 88 mm (D x W x H)
<b>Weight</b>	7.9Kg

<b>Temperature</b>	0 ~ 50°C (Operating), -10 ~ 70°C (Storage)
<b>Humidity</b>	10 ~ 90% non-condensing
<b>Certification</b>	CE, FCC
<b>MTBF</b>	65,000 hrs

### Application



Easy to install or remove without any tools

**FMC-CH17 Front view**

- FMC Option Converters
- Fast Ethernet
  - Gigabit Ethernet
  - VDSL2 LAN Extender



**FMC-CH17 Back view**



**Note:** Each FMC Card can be placed in the FMC-CH17 chassis, also can use the wall mount kit for rack mount installation.



**FMC-WMK01** (Single Unit Wall Mounting Kit)

### Ordering Information

Model Name	Description
FMC-CH17-AC, DC, AD, AA, DD	2U, 19", 17-Slot FMC Converter Chassis with AC, DC, AD, AA or DD power

### Optional Accessories

Wall Mount Kits	Type
FMC-WMK01	Single Unit Wall Mounting Kit