

Serial Cables

Serial connection cables

Features and Benefits

- Extend the transmission distance of serial signals



Introduction


Moxa's serial cables extend the transmission distance for your multiport serial cards. It also expands the serial com ports for a serial connection.

Pin Assignments


CBL-M44M9x4-50




RS-232



RS-422/RS-485-4w




RS-485-2w




CBL-M44M25x4-50




RS-232




RS-422/RS-485-4w




RS-485-2w




CBL-RJ45F9-150




CBL-RJ45M25-150




CBL-RJ45F9-150




CBL-RJ45M25-150




CBL-RJ45M9-150




CBL-RJ45SF25-150




CBL-RJ45SF9-150




CBL-RJ45SM25-150




CBL-RJ45SM9-150




CN20030




CN20040



CN20060



CN-20070



Specifications

Connector

Board-side Connector	<p> CBL-F9M9-20: DB9 (female) x 1 CBL-F9M9-150: DB9 (female) x 1 CBL-HSF2x10-15: 20-pin (female) x 1 CBL-M9HSF1x10H-15-01: 10-pin (female) x 1 CBL-M9HSF1x10H-15-02: 10-pin (female) x 1 CBL-M9x2HSF2x10H-15: 20-pin (female) x 1 CBL-M25M9x2-50: DB25 (male) x 1 CBL-M44M25x4-50: DB44 (male) x 1 CBL-M44M9x4-50: DB44 (male) x 1 CBL-M62M25x8-100: DB62 (male) x 1 CBL-M62M9x8-100: DB62 (male) x 1 CBL-M68M25x8-100: VHDCI 68 x 1 CBL-M68M9x8-100: VHDCI 68 x 1 CBL-M78M25x8-100: DB78 (male) x 1 CBL-M78M9x8-100: DB78 (male) x 1 CBL-RJ45F9-150: 8-pin RJ45 x 1 CBL-RJ45F25-150: 8-pin RJ45 x 1 CBL-RJ45M9-150: 8-pin RJ45 x 1 CBL-RJ45M25-150: 8-pin RJ45 x 1 CBL-RJ45SF9-150: 8-pin RJ45 x 1 CBL-RJ45SF25-150: 8-pin RJ45 x 1 CBL-RJ45SM9-150: 8-pin RJ45 x 1 CBL-RJ45SM25-150: 8-pin RJ45 x 1 CBL-USBAP-50: USB Type A x 1 CN20030: 10-pin RJ45 x 1 CN20040: 10-pin RJ45 x 1 CN20060: 10-pin RJ45 x 1 CN20070: 10-pin RJ45 x 1 NP21101: DB25 (male) x 1 NP21102: DB25 (male) x 1 NP21103: DB25 (male) x 1 </p>
Device-side Connector	<p> CBL-F9M9-20: DB9 (male) x 1 CBL-F9M9-150: DB9 (male) x 1 CBL-HSF2x10-15: 20-pin (female) x 1 CBL-M9HSF1x10H-15-01: DB9 male x 1 CBL-M9HSF1x10H-15-02: DB9 male x 1 CBL-M9x2HSF2x10H-15: DB9 male x 2 CBL-M25M9x2-50: DB9 (male) x 2 CBL-M44M25x4-50: DB25 (male) x 4 CBL-M44M9x4-50: DB9 (male) x 4 CBL-M62M25x8-100: DB25 (male) x 8 CBL-M62M9x8-100: DB9 (male) x 8 CBL-M68M25x8-100: DB25 (male) x 8 CBL-M68M9x8-100: DB9 (male) x 8 CBL-M78M25x8-100: DB25 (male) x 8 CBL-M78M9x8-100: DB9 (male) x 8 CBL-RJ45F9-150: DB9 (female) x 1 CBL-RJ45F25-150: DB25 (female) x 1 CBL-RJ45M9-150: DB9 (male) x 1 CBL-RJ45M25-150: DB25 (male) x 1 CBL-RJ45SF9-150: DB9 (female) x 1 CBL-RJ45SF25-150: DB25 (female) x 1 CBL-RJ45SM9-150: DB9 (male) x 1 CBL-RJ45SM25-150: DB25 (male) x 1 CBL-USBAP-50: DC Jack x 1 CN20030: DB25 (female) x 1 CN20040: DB25 (male) x 1 CN20060: DB9 (male) x 1 CN20070: DB9 (female) x 1 NP21101: DB9 (female) x 1 NP21102: DB9 (male) x 1 NP21103: Terminal block x 1 </p>

Physical Characteristics

Cable Length	CBL-F9M9-20: 20 cm (7.87 in) CBL-F9M9-150: 150 cm (4.9 ft) CBL-HSF2x10-15: 15 cm (0.49 ft) CBL-M9HSF1x10H-15-01: 15 cm (0.49 ft) CBL-M9HSF1x10H-15-02: 15 cm (0.49 ft) CBL-M9x2HSF2x10H-15: 15 cm (0.49 ft) CBL-M25M9x2-50: 50 cm (19.69 in) CBL-M44M9x4-50: 50 cm (19.69 in) CBL-M44M25x4-50: 50 cm (19.69 in) CBL-M62M9x8-100: 100 cm (3.3 ft) CBL-M62M25x8-100: 100 cm (3.3 ft) CBL-M68M9x8-100: 100 cm (3.3 ft) CBL-M68M25x8-100: 100 cm (3.3 ft) CBL-M78M9x8-100: 100 cm (3.3 ft) CBL-M78M25x8-100: 100 cm (3.3 ft) CBL-RJ45F9-150: 150 cm (4.9 ft) CBL-RJ45F25-150: 150 cm (4.9 ft) CBL-RJ45SM9-150: 150 cm (4.9 ft) CBL-RJ45SM25-150: 150 cm (4.9 ft) CBL-RJ45SF9-150: 150 cm (4.9 ft) CBL-RJ45SF25-150: 150 cm (4.9 ft) CBL-RJ45M9-150: 150 cm (4.9 ft) CBL-RJ45M25-150: 150 cm (4.9 ft) CN20030: 150 cm (4.9 ft) CN20040: 150 cm (4.9 ft) CN20060: 150 cm (4.9 ft) CN20070: 150 cm (4.9 ft) NP21101: 30 cm (11.81 in) NP21102: 30 cm (11.81 in) CBL-USBAP-50: 50 cm (19.69 in)
--------------	--

Ordering Information

Model Name	Board-side Connectors	Device-side Connectors	Cable Length
CBL-F9M9-20	1 x DB9 (female)	1 x DB9 (male)	20 cm
CBL-F9M9-150	1 x DB9 (female)	1 x DB9 (male)	150 cm
CBL-M62M25x8-100	1 x DB62 (male)	8 x DB25 (male)	100 cm
CBL-M62M9x8-100	1 x DB62 (male)	8 x DB9 (male)	100 cm
CBL-M68M25x8-100	1 x VHDCI 68	8 x DB25 (male)	100 cm
CBL-M68M9x8-100	1 x VHDCI 68	8 x DB9 (male)	100 cm
CBL-M78M25x8-100	1 x DB78 (male)	8 x DB25 (male)	100 cm
CBL-M78M9x8-100	1 x DB78 (male)	8 x DB9 (male)	100 cm
CBL-M25M9x2-50	1 x DB25 (male)	2 x DB9 (male)	50 cm
CBL-M44M25x4-50	1 x DB44 (male)	4 x DB25 (male)	50 cm
CBL-M44M9x4-50	1 x DB44 (male)	4 x DB9 (male)	50 cm
CBL-RJ45F25-150	1 x 8-pin RJ45	1 x DB25 (male)	150 cm
CBL-RJ45F9-150	1 x 8-pin RJ45	1 x DB9 (female)	150 cm
CBL-RJ45M25-150	1 x 8-pin RJ45	1 x DB25 (male)	150 cm
CBL-RJ45M9-150	1 x 8-pin RJ45	1 x DB9 (male)	150 cm
CBL-RJ45SF25-150	1 x 8-pin RJ45	1 x DB25 (male)	150 cm
CBL-RJ45SF9-150	1 x 8-pin RJ45	1 x DB9 (male)	150 cm
CBL-RJ45SM25-150	1 x 8-pin RJ45	1 x DB25 (male)	150 cm
CBL-RJ45SM9-150	1 x 8-pin RJ45	1 x DB9 (male)	150 cm

Model Name	Board-side Connectors	Device-side Connectors	Cable Length
CBL-M12D(MM4P)/RJ45-100 IP67	1 x M12	1 x 8-pin RJ45	100 cm
CBL-M9HSF1x10H-15-01	1 x 10-pin housing cable (female)	1 x DB9 (male)	15 cm
CBL-M9HSF1x10H-15-02	1 x 10-pin housing cable (female)	1 x DB9 (male)	15 cm
CBL-M9x2HSF2x10H-15	1 x 20-pin housing cable (female)	2 x DB9 (male)	15 cm
CBL-HSF2x10-15	1 x 20-pin housing cable (female)	1 x 20-pin housing cable (female)	15 cm
CN20030	1 x 10-pin RJ45	1 x DB25 (female)	150 cm
CN20040	1 x 10-pin RJ45	1 x DB25 (male)	150 cm
CN20060	1 x 10-pin RJ45	1 x DB9 (male)	150 cm
CN20070	1 x 10-pin RJ45	1 x DB9 (female)	150 cm
NP21101	1 x DB25 (male)	1 x DB9 (female)	150 cm
NP21102	1 x DB25 (male)	1 x DB9 (male)	150 cm
NP21103	1 x DB25 (male)	1 x Terminal block	–
20P To 20P Flat Cable-500mm	1 x 20-pin connector	1 x 20-pin connector	50 cm
CBL-USBAP-50	1 x Type A	1 x DC jack	50 cm
CBL-USBAB-100	1 x Type A	1 x Type B	100 cm

© Moxa Inc. All rights reserved. Updated Apr 18, 2023.

This document and any portion thereof may not be reproduced or used in any manner whatsoever without the express written permission of Moxa Inc. Product specifications subject to change without notice. Visit our website for the most up-to-date product information.